

4K@144  
10Gbps USB

# PAAG-ET3122B



## 2 Ports Dual Monitor 8K DisplayPort 1.4 KVM Switch with USB 3.2 Gen 2, Audio, Hotkey Control

### ► Specifications

Model Number		PAAG-ET3122B
MAX. Resolution		7680x4320@60Hz ( 4:4:4 ) ( DSC ) 7680x4320@30Hz ( 4:4:4 ) 5120x1440@120Hz ( 4:4:4 ) 4096x2160@144Hz ( 4:4:4 )
Computer Interface ( 2-Port )	USB 3.2 Gen 2 Ports	USB-C x 2
	Video Input	DisplayPort 1.4 x 4
	Audio Input	3.5mm Speaker Jack x 2
Console Interface	USB 3.2 Gen 2 Ports	USB-A x 1 ( Front ) USB-A x 1 ( Rear )
	USB HID Ports	USB-A x 1 ( Front ) USB-A x 3 ( Rear )
	Video Output	DisplayPort 1.4 x 2
	Audio Output	3.5mm Speaker Jack x 1
Control Methods		Hotkey / Push Button
HDCP Compliance		HDCP 2.2 and HDCP 1.4
Hot Plug-and-Play		Yes
Push Buttons		Port-Select x 1
LED Indicators		PC-Ready x 2, PC-Select x 2
Power supply		DC 9~12V
Operation Environment		0~40°C, Humidity<80%
Storage Temperature		-20~60°C
H x W x D ( mm )		60 x 160 x 100
Material		Metal
Weight ( g )		725



### ► Features

- Allows 2 Computers Share 1 Set of KVM Console
- Dual-Monitor Design Fulfills User's Optimum Work-Efficiency
- DisplayPort 1.4 Video Supports Most Popular Resolutions Up to 4K@144Hz, 5K@120Hz, and 8K@60Hz ( 4:4:4 ) ( DSC )
- HDR10 Support for Best Visual Experience
- HDCP 2.2 and HDCP 1.4 Compliance
- DisplayPort 1.4 Standard Features Compliance :
  - VRR ( Variable Refresh Rate ) for Gaming
  - DSC ( Display Stream Compression ) Allows Even Higher Resolutions
  - HFR ( High-Frame-Rate ) Allows Best Performance in High Dynamic Videos
  - MST ( Multi-Stream Technology ) Allows Expansion to More Monitor Numbers
- 2 Flexible Switching Control Methods :
  - Front Push Buttons
  - Hotkey Control
- Plug-and-Play without Software or Driver
- Front and Rear USB Ports Allow Easy Access
- USB 3.2 Gen 2 Provides Excellent 10Gbps Speed
- Suitable Applications Includes Office, SOHO, Gaming, Industrial Control, and Video Wall Switching

### ► Overview

The **2 Ports Dual Monitor 8K DisplayPort 1.4 KVM Switch**, PAAG-ET3122B, allows 2 computers to share 1 set of KVM console, including DisplayPort 1.4 monitors ( Dual-monitor ), Hotkey Control, 3.5mm speaker, and USB 3.2 Gen 2 devices.

### ► Product Family

Product Number	Ports	Video Interface	USB Ports
PAAG-ET3112B	2	DisplayPort 1.4	USB 3.2 Gen 2, 10Gbps
PAAG-ET3122B		Dual DisplayPort 1.4	
PAAG-ET3132B		Triple DisplayPort 1.4	
PAAG-ET3142B		Quad DisplayPort 1.4	

\*Certain Models Available Upon Bulk Orders

### ► Connection pattern

